



Using Agilent 6690A Series System dc Power Supplies for Automobile Battery Simulation

Product Note 6690A-2

Minimize your testing downtime with this reliable, high power dc supply

- Low ripple & noise
- Fast up-and-down programming
- High accuracy current programming and read back
- Industry standard SCPI programming commands
- Analog programming
- Analog monitoring
- Full protection from overcurrent, overvoltage, overtemperature
- Remote sense
- Electronic calibration
- Standard 3-year warranty

In the past few years, the electronic content of automobiles has been increasing at a fast rate, resulting in higher battery currents. Combine that with efforts to improve efficiency; today's 12 V car battery is just not adequate for the cars of the future. The trend is for higher



voltage, which will lower the current, resulting in savings in the wiring harness and other components used in cars.

42 V is becoming standard voltage for the battery. However, because of load changes during the operation of the vehicle, that voltage may reach up to 60 V or go as low as 25 V. The new 42 V battery will have different requirements for duty cycle and total power capability than the 12 V battery. Under the start/stop scenario of the future vehicles, the number of starts and stops that the battery will

endure could increase by a factor of more than 10. This loading puts more strain on the battery and other components used in the car. The Agilent 6692A power supply is ideal for simulating the battery under all loading conditions. This power supply can also be used to test electronic equipment while simulating actual battery voltage fluctuations.



Agilent Technologies

During the developmental phase, Agilent power supplies undergo a battery of environmental tests such as an 8-day temperature profile. Other tests include humidity, altitude, shock and vibration, ESD, ac line tests, EMC and RFI. The power supplies are designed with built-in margin so that they can meet their specifications over time, under all conditions, and also withstand peak stress.

Wide design margins and stringent environmental tests translate into reliable products. To you, it means lower cost of ownership, minimum downtime and faster delivery of your electronic equipment/components to your customers.

Agilent Technologies' Test and Measurement Support, Services, and Assistance

Agilent Technologies aims to maximize the value you receive, while minimizing your risk and problems. We strive to ensure that you get the test and measurement capabilities you paid for and obtain the support you need. Our extensive support resources and services can help you choose the right Agilent products for your applications and apply them successfully. Every instrument and system we sell has a global warranty. Support is available for at least five years beyond the production life of the product. Two concepts underlie Agilent's overall support policy: "Our Promise" and "Your Advantage."

Our Promise

"Our Promise" means your Agilent test and measurement equipment will meet its advertised performance and functionality. When you are choosing new equipment, we will help you with product information, including realistic performance specifications and practical recommendations from experienced test engineers. When you use Agilent equipment, we can verify that it works properly, help with product operation, and provide basic measurement assistance for the use of specified capabilities, at no extra cost upon request. Many self-help tools are available.

Your Advantage

"Your Advantage" means that Agilent offers a wide range of additional expert test and measurement services, which you can purchase according to your unique technical and business needs. Solve problems efficiently and gain a competitive edge by contracting with us for calibration, extra-cost upgrades, out-of-warranty repairs, and on-site education and training, as well as design, system integration, project management, and other professional services. Experienced Agilent engineers and technicians worldwide can help you maximize your productivity, optimize the return on investment of your Agilent instruments and systems, and obtain dependable measurement accuracy for the life of those products.

Get assistance with all your test and measurement needs at:
www.agilent.com/find/assist

Product specifications and descriptions in this document subject to change without notice.

Copyright © 2001 Agilent Technologies
 Printed in U.S.A. October 21, 2001
 5988-3061EN

Specifications

Parameter	Agilent Model Number			
	6690A	6691A	6692A	
Output Ratings				
Voltage:	0 - 15 V	0 - 30 V	0 - 60 V	
Current:*	0 - 440 A	0 - 220 A	0 - 110 A	
*Derated linearly 1%/°C from 40°C to 55°C				
Programming Accuracy (@ 25 ±5°C)				
Voltage:	0.04% +	15 mV	30 mV	60 mV
Current:	0.1% +	230 mA	125 mA	65 mA
Ripple & Noise (from 20 Hz to 20 MHz with outputs ungrounded, or with either output terminal grounded)				
Constant Voltage:	rms	2.5 mV	2.5 mV	2.5 mV
Constant Voltage:	p-p	15 mV	25 mV	25 mV
Constant Current:**	rms	200 mA	50 mA	30 mA
**With load inductance >5µH.				
Readback Accuracy (from front panel or over GPIB with respect to actual output @ 25 ±5°C)				
Voltage:	0.05% +	22.5 mV	45 mV	90 mV
±Current	0.1% +	300 mA	165 mA	80 mA
Load Regulation (change in output voltage or current for any load change within ratings)				
Voltage:	0.002% +	650 µV	1.1 mV	2.2 mV
Current:	0.005% +	40 mA	17 mA	9 mA
Line Regulation (change in output voltage or current for any line change within ratings)				
Voltage:	0.002% +	650 µV	650 µV	650 µV
Current:	0.005% +	40 mA	17 mA	9 mA
Transient Response Time (for the output voltage to recover to within 150 mV following any step change from 100% to 50% or 50% to 100% of the rated output current): <900 µs				

For more information regarding Agilent's dc power supplies, visit our Web site at: <http://www.agilent.com/find/power>